



## Requirements

1. Fully configured Player Portfolio
  - Setup & functional via Nuvo Player app
2. Control4 Controller
  - Recommend update to latest OS
3. Control4 Composer
  - Recommend update to latest version

## Configure Composer Project File:

1. Open Composer
2. Navigate to: System Design>Items>Search
  - Select "Online/Certified Only"
  - Type "nuvo" into the search parameter field
3. Select - Any Room & Double-Click **"Nuvo Virtual Matrix"**
4. Navigate to: System Design>Items>Discovered
5. Launch the Nuvo Player App
  - Navigate to: Settings>General>About
  - Record the MAC Address of each zone
6. Select - A Specific Room to add a zone player to
7. Double-Click **"Nuvo-Pxxxx"**
  - *Rename Player & Endpoint (optional)*
  - Repeat steps 7 & 8 for all additional rooms/zones you wish to add
8. Navigate to: System Design>Room>Navigator>Listen>Modify
  - Move ALL other zone players & endpoints to [Hidden Devices](#)
  - Repeat for all additional room navigators
9. Navigate to: System Design>Room>Navigator>Watch>Modify
  - Move ALL zone players & endpoints to [Hidden Devices](#)
  - Repeat for all additional room navigators
10. Select - File>Refresh Navigators



## Grouping:

To group zones via programming (i.e. adding a “Party” button on a UI that starts multiple zones in sync, you must first create a Media Scene.

## Requirements:

The “Top 10” must be programmed in the Nuvo Player App

## Creating a “Group” Media Scene:

1. Open Composer
2. Navigate to: Agents>Media Scenes
3. Add a Media Scene
4. [NAME] the New Scene (i.e. “Party”)
5. Select “Add Room”
6. Select the rooms you want included in the scene & click “OK”
7. Set the “Initial Volume” for each room

## Activating the Media Scene [NAME] from a keypad:

1. Navigate to: Programming - Select Configurable Keypad
2. In the Programming Pane>Keypad Events>Events For: Select the button you want to program & select Single Tap
3. In the Actions Pane>Device Actions - Select the room you want to be the [MASTER]
4. In the Actions Pane>Device Actions>[MASTER] Actions>Select an Audio Device - Select the Nuvo Player for that room from the dropdown list & Double-Click the “Action” to add it to the “Script”
5. In the Actions Pane>Device Actions>“Nuvo Player” Actions - Select Device Specific Command, Select “Slot 1-10 from the dropdown list & Double-Click the “Action” to add it to the “Script”
6. In the Actions Pane>Device Actions>Media Scenes Actions>Commands - Select Activate, Based on: [MASTER], Media Scenes [NAME] & Double-Click the “Action” to add it to the “Script”

## Deactivating the Media Scene [NAME]:

1. Navigate to: Programming - Select Configurable Keypad, Custom Buttons etc...
2. In the Programming Pane>Keypad Events>Events For: Select the button you want to program & select Double Tap
3. In the Actions Pane>Device Actions>[MASTER] Actions>Select “Commands” Pause & Double-Click the “Action” to add it to the “Script”
4. In the Actions Pane>Device Actions>Media Scenes Actions>Commands - Select Deactivate & Double-Click the “Action” to add it to the “Script”

**Note: In the Nuvo Player App>Settings>General>Advanced you MUST turn on Auto Disband Inactive Groups & define the Auto Disband Timeout.**