


Pass and Seymour

Turnlok® Portable 2-Foot In-Line 15A Self-Test GFCI with Plug and Connector, Automatic Reset





The perfect option for safely powering portable equipment, outdoors or in, when a GFCI-protected outlet is not accessible. Use this 2-Foot In-Line Portable GFCI (Automatic Reset) when plugging in drills, saws, leaf blowers, pressure washers, power painters, etc. for protection against electrical shock caused by ground-faults.

Designed with Legrand's Turnlok connector to lock plugs in place, preventing accidental disconnection for safer, more reliable operation.

GFCI protection is required by code in bathrooms, kitchens, garages, outdoor areas, and for any other outlets found within six feet of a sink or water source.

Features & Benefits

Protects against electrical shock caused by ground-fault occurrences.

Equipped with proven SafeLock protection feature: if critical components are damaged and protection is lost, power to the outlet is disconnected.

Automatically energizes portable GFCI for use upon plugin and after loss of primary power.

Conducts an industry-leading automatic self-test every 3 seconds. If the portable GFCI device ever fails, the red indicator light flashes to signal it should be replaced.

Open neutral relay automatically cuts power to device line conductor if the neutral wire preceding the portable GFCI becomes damaged.

Specifications

General Info				
Product Line	Pass & Seymour	Color	Black	
Finish	Matte	UPC Number	785007381665	
Country Of Origin	China	Outlet Type	GFCI	
Application Sector	Commercial, Residential	Warranty Type	1-Year Limited Warranty	
Dimensions				
Product Width US	2.0 in	Product Weight US	1.0 lb	
Product Depth US	1.75 in	Product Length US	27.75 in	

Listing Agencies / 3rd Party Agencies

cULus ListingNumber	943	cULus Listed	Yes
Additional Information			
RoHS Compliant	Yes		
Technical Information			
Seismic Tested	No	Is Tamper-Resistant	No
Amperage	15 A	Is Weather Resistant	No
Indoor/Outdoor	Outdoor		