

adorne Collection adorne® Pop-Out Outlet with Magnesium Wall Plate, Magnesium Part No. ARPTR151GM2WP



The cleverest way to add power and style, the Pop-Out Outlet extends to offer 3-plug access, then uniquely disappears back into the wall with a simple push when not in use. Made exclusively for use with screwless Wall Plates from the adorne® Collection, sold separately.

Features & Benefits

For complete installation, device must be paired with an adorne® screwless Wall Plate (not included). Available in a range of contemporary colors and stunning finishes.	Perfect anywhere you'd like to hide outlets when not in use, for added style and safety.
Provides additional power with 3-plug access when extended from wall.	Disappears back into the wall with a simple push when not needed.
Installs easily in as little as 15 minutes.	Comes with a special frame for mounting and requires a deep electrical outlet (22.5 cubic inches). No new wires required for typical installation.
Protects children with a patented tamper-resistant shutter system that prevents improper insertion of foreign objects, complete with "invisi-shutters" for an invisible offect	More color options available to fit any style, including finishes to match current hardware and lighting trends.

Specifications

"invisi-shutters" for an invisible effect.

General Info

Product Line	Pass & Seymour	Color	Magnesium
UPC Number	785007158465	Country Of Origin	China
Number of Receptacles	3	Features	Pop-Out
Outlet Type	Pop-Out, Tamper-Resistant	Application Sector	Multi-Dwelling Unit, Residential
Wall Plate Included	Yes	Warranty Type	Limited Lifetime Warranty
Dimensions			
Product Width US	3.45 in	Product Depth US	2.6 in

Product Height US	5.13 in		
Technical Information			
Is Tamper-Resistant	Yes	Connection Location	Back Only
Number of Wires	3	Number of Gangs	1
Amperage	15 A	Number of Poles	Double Pole
Wire Size	14 - 12 AWG	Indoor/Outdoor	Indoor
Mounting Type	Box	Wire Connection Type	Internal Pressure Plates

Connection Type

Internal Pressure Plates

Voltage

125.0 V