



Wattstopper
Discontinued - PIR Wall Switch Occupancy Sensor, 120/277V, Black
Part No. PW-100-B



The PW-100 passive infrared (PIR) wall switch sensor can turn lights OFF and ON based on occupancy. It is characterized by high sensitivity to small and large movements, appealing aesthetics, and a variety of features.

Features & Benefits

| | |
|---|--|
| High sensitivity and dense coverage for exceptional performance | No neutral wire required |
| Color-matched lens and low profile for appealing design | Selectable operation, walk-through, test and presentation modes for increased energy savings and convenience |
| Defaults to Manual-ON operation for maximum energy savings. | Defaults to Manual-ON operation for maximum energy savings. |

Specifications

General Info

| | | | |
|-------------------|---------------|-------------------------|------------------------------|
| Product Line | Wattstopper | Replaced by Part Number | PW-301-B |
| Color | Black | UPC Number | 754182919260 |
| Country Of Origin | China | Features | IR (Infrared), Motion Sensor |
| Switch Type | Motion Sensor | Application Sector | Commercial |
| Warranty Type | 5-Year | | |

Dimensions

| | | | |
|-------------------|------------|-------------------|--------|
| Product Width US | 4.0 in | Product Weight US | 0.3 lb |
| Product Volume US | 63.0 cu in | Product Depth US | 5.0 in |

| | |
|-------------------|---------|
| Product Height US | 3.15 in |
|-------------------|---------|

Additional Information

| | |
|-------------------------------|-----|
| Product Environmental Profile | Yes |
|-------------------------------|-----|

Technical Information

| | | | |
|--------------------|---|-------------|-----------|
| Response Frequency | 50/60 Hz | Sensor Type | Occupancy |
| Number of Buttons | 1 | Amperage | 4.3 A |
| Indicator | LED Light | Wattage | 1200 W |
| Sensing Range | Major motion 35 x 30 ft,Minor motion 20 x 15 ft | Voltage | 120/277 V |
| Connection Type | Wired | | |