



The PW-101 passive infrared (PIR) wall switch sensor can turn lights OFF and ON based on occupancy. It is characterized by high sensitivity to small and large movements, appealing aesthetics, and a variety of features.

Features & Benefits

Detection Signature Processing eliminates false triggers and provides immunity to RFI and EMI	Zero-crossing for long relay life
Vandal resistant lens combines precise coverage with durability	Choice of Manual-ON or Auto-ON operation
Selectable walk-through mode turns lights off three minutes after the room is initially occupied if no motion is detected after the first 30 seconds	Test mode allows quick and easy adjustments
Selectable audible and/or visual alerts for impending shutoff	In automatic mode, sensor returns automatically to Auto-ON after lights are turned off manually; ideal for presentations
LED indicates occupancy detection	Optional light level sensing with simple setup
Service mode allows sensor to operate as a service switch in the unlikely event of a failure	Neutral required to meet NEC 2011 code
Sensor coverage tested to NEMA Guide Publication WD 7-2000	Compatible with decorator wall plates

Specifications

General Info

Product Line	Wattstopper	Replaced by Part Number	PW-301-W
Color	White	UPC Number	754182923502
Country Of Origin	China	Features	IR (Infrared), Motion Sensor
Switch Type	Motion Sensor	Application Sector	Commercial
Warranty Type	5-Year		

Technical Information

Response Frequency	50/60 Hz	Sensor Type	Occupancy
Number of Gangs	1	Number of Buttons	1
Indicator	LED Light	Mounting Type	Box

Sensing Range	Major motion 35 x 30 ft. Minor motion 20 x 15 ft	Voltage	120/277 V
---------------	---	---------	-----------

Connection Type	Wired
-----------------	-------
