



Wattstopper Discontinued - PIR Wall Switch Occupancy Sensor, 120/277V, Red Part No. PW-200-R



The PW-200 passive infrared (PIR) wall switch sensor turns lights ON and OFF based on occupancy. It contains two relays for controlling two independent lighting loads or circuits, and a variety of features.

Features & Benefits

High sensitivity and dense coverage for exceptional performance

Color-matched lens and low profile for appealing design

Defaults to Auto-ON to 50% operation for maximum energy savings

Two relays for control of two separate lighting loads or circuits

Selectable operation, walk-through, test and presentation modes for increased energy savings and convenience

Defaults to Auto-ON to 50% operation for maximum energy savings

Specifications

General Info

Product Line	Wattstopper	Replaced by Part Number	PW-302-R
Color	Red	UPC Number	754182934430
Country Of Origin	China	Features	IR (Infrared), Motion Sensor
Switch Type	Motion Sensor	Application Sector	Commercial
Warranty Type	5-Year		

Dimensions

Product Width US	4.0 in	Product Weight US	0.3 lb
Product Volume US	63.0 cu in	Product Depth US	5.0 in

Product Height US 3.15 in

Additional Information

Product Environmental Profile Yes

Technical Information

Response Frequency	50/60 Hz	Sensor Type	Occupancy
--------------------	----------	-------------	-----------

Number of Buttons	2	Amperage	4.3 A
-------------------	---	----------	-------

Indicator	LED Light	Wattage	1200 W
-----------	-----------	---------	--------

Sensing Range	Major motion 35 x 30 ft, Minor motion 20 x 15 ft	Voltage	120/277 V
---------------	--	---------	-----------

Connection Type	Wired
-----------------	-------
