



Wattstopper
Discontinued - PIR Wall Switch Occupancy Sensor, 120/277V, Red
Part No. PW-200-R



The PW-200 passive infrared (PIR) wall switch sensor turns lights ON and OFF based on occupancy. It contains two relays for controlling two independent lighting loads or circuits, and a variety of features.

Features & Benefits

High sensitivity and dense coverage for exceptional performance

Color-matched lens and low profile for appealing design

Defaults to Auto-ON to 50% operation for maximum energy savings

Two relays for control of two separate lighting loads or circuits

Selectable operation, walk-through, test and presentation modes for increased energy savings and convenience

Defaults to Auto-ON to 50% operation for maximum energy savings

Specifications

General Info

Product Line	Wattstopper	Replaced by Part Number	PW-302-R
Color	Red	UPC Number	754182934430
Country Of Origin	China	Features	IR (Infrared), Motion Sensor
Switch Type	Motion Sensor	Application Sector	Commercial
Warranty Type	5-Year		

Dimensions

Product Width US	4.0 in	Product Weight US	0.3 lb
Product Volume US	63.0 cu in	Product Depth US	5.0 in

Product Height US	3.15 in
-------------------	---------

Additional Information

Product Environmental Profile	Yes
-------------------------------	-----

Technical Information

Response Frequency	50/60 Hz	Sensor Type	Occupancy
Number of Buttons	2	Amperage	4.3 A
Indicator	LED Light	Wattage	1200 W
Sensing Range	Minor motion 20 x 15 ft, Major motion 35 x 30 ft	Voltage	120/277 V
Connection Type	Wired		