



**Wattstopper**  
**PIR Wall Switch Occupancy Sensor, 347V, Red**  
Part No. PW-302-347-R



The PW-302 passive infrared (PIR) wall switch sensor turns lights ON and OFF based on occupancy. It contains two relays for controlling two independent lighting loads or circuits, and a variety of features.

## Features & Benefits

High sensitivity and dense coverage for exceptional performance

Two relays for control of two separate lighting loads or circuits

Defaults to Auto-ON to 50% operation for maximum energy savings

Optional neutral connection with break off tab to expose neutral terminals

120/240/277 VAC and 347 VAC models

Allows multi-way control from one of up to four control locations

## Specifications

### General Info

Product Line	Wattstopper	Color	Red
UPC Number	754182935611	Country Of Origin	China

### Dimensions

Product Width US	1.8 in	Product Weight US	0.3 lb
Product Volume US	35.1 cu in	Product Depth US	1.8 in
Product Height US	4.5 in		

### Technical Information

Sensor Type	Occupancy	Amperage	4.3 A
Wattage	1500 W	Voltage	347 V