



Wattstopper
PIR Wall Switch Occupancy Sensor
Part No. PW-302-IU



The PW-302 passive infrared (PIR) wall switch sensor turns lights ON and OFF based on occupancy. It contains two relays for controlling two independent lighting loads or circuits, and a variety of features.

Features & Benefits

High sensitivity and dense coverage for exceptional performance

Two relays for control of two separate lighting loads or circuits

Defaults to Auto-ON to 50% operation for maximum energy savings

Optional neutral connection with break off tab to expose neutral terminals

120/240/277 VAC and 347 VAC models

Allows multi-way control from one of up to four control locations

Specifications

General Info

Product Line	Wattstopper	Color	Ivory
UPC Number	754182938537	Country Of Origin	United States

Technical Information

Sensor Type	Occupancy	Amperage	4.3 A
Wattage	1200 W	Voltage	120/277 V