



**Wattstopper**  
**0-10V PIR Wall Switch Occupancy Sensor, 347V, Black**  
Part No. PW-311-347-B



The PW-311 passive infrared (PIR) dimming wall switch sensor can turn lights OFF and ON based on occupancy and allow the user to increase or decrease the lighting level. It works with 0-10 VDC dimming drivers and ballasts to control lighting loads including LEDs.

## Features & Benefits

Defaults to Manual-ON operation for maximum energy savings Neutral Sense™ connection option with break off tab to expose neutral terminals

Color-matched lens and low profile for appealing design

Supports Partial-ON operation for energy code compliance or incentives

120/240/277VAC and 347VAC models

Allows fully functional multi-way control from up to four switch locations

## Specifications

### General Info

Product Line	Wattstopper	Color	Black
UPC Number	754182939077		

### Dimensions

Product Width US	4.0 in	Product Weight US	0.55 lb
Product Volume US	36.07 cu in	Product Depth US	3.03 in
Product Height US	2.48 in		

### Technical Information

Sensor Type	Occupancy	Amperage	4.3 A
-------------	-----------	----------	-------

---

Wattage

1500 W

Voltage

347.0 V

---