Wattstopper

0-10V PIR Wall Switch Occupancy Sensor, 120/277V, Black

Part No. PW-311-B



The PW-311 passive infrared (PIR) dimming wall switch sensor can turn lights OFF and ON based on occupancy and allow the user to increase or decrease the lighting level. It works with 0-10 VDC dimming drivers and ballasts to control lighting loads including LEDs.

Features & Benefits

- Vandal resistant lens combines precise coverage with durability
- Optional Smart Light Level adapts ambient light hold off threshold to meet user needs
- Test mode allows quick and easy verification of coverage
- LED indicates occupancy detection
- Presentation mode may be deactivated to allow Auto-ON operation after 15 second time delay
- Selectable walk-through mode turns lights off three minutes after the room is initially occupied if no motion is detected after the first 30 seconds
- Selectable audible and/or visual alerts for impending shutoff

Specifications

General Info

Product Line	Wattstopper	Color	Black
UPC Number	754182939022	Country Of Origin	China
Features	IR (Infrared), Motion Sensor	Switch Type	Motion Sensor
Application Sector	Commercial		

Dimensions

Product Width US	4.0 in	Product Weight US	0.48 lb
Product Volume US	36.07 cu in	Product Depth US	3.03 in

Product Height US	2.48 in

Additional Information

RoHS Conformant	Yes	DesignLights Consortium Qualified System	Yes
Security	Yes		

Technical Information

Response Frequency	50/60 Hz	Sensor Type	Occupancy
Number of Buttons	3	Amperage	4.3 A
Wattage	1200 W	Mounting Type	Box
Sensing Range	180 degrees, 1050 sq ft	Voltage	120/277 V
Connection Type	Wired	Load	1000W