



The RS-250 Passive Infrared (PIR) Occupancy Sensor provides automatic lighting shutoff for single-pole lighting control applications.

Features & Benefits

- | | |
|---|--|
| Lighted switch for visibility in darkened rooms | Fixed five-minute time delay |
| Low-profile styling with uniform, color-matched lens and device | With the RS-150U option, no leakage to load in off mode for safety |
| Replaces standard light or fan single-pole switches | Automatic-on operation |

Specifications

General Info

| | | | |
|--------------------|----------------|--------------------|---|
| Product Line | Pass & Seymour | Color | Black |
| Finish | Matte | UPC Number | 754182917556 |
| Country Of Origin | China | Features | IR (Infrared), Locator Light, Motion Sensor |
| Switch Type | Motion Sensor | Number of Switches | 1 |
| Application Sector | Residential | Warranty Type | 5-Year |
| Type | Switch | | |

Dimensions

| | | | |
|-------------------|---------|-------------------|---------|
| Product Width US | 1.69 in | Product Depth US | 1.88 in |
| Product Height US | 2.63 in | Product Length US | 2.63 in |

Technical Information

| | | | |
|--------------------|--------------------------------|-----------------------|-------------|
| Seismic Tested | No | Response Frequency | 60 Hz |
| Sensor Type | Occupancy | Number of Buttons | 1 |
| Bulb Compatibility | CFL, Fluorescent, Incandescent | Number of Poles | Single Pole |
| Wire Size | #14 - #10 AWG | Requires Neutral Wire | Yes |
| Indoor/Outdoor | Indoor | Wattage | 600 W |
| Mounting Type | Box | Voltage | 120.0 V |
| Connection Type | Wired | | |