



Pass and Seymour
Discontinued - 600W 120V Single Pole/3-Way Occupancy/Vacancy Sensor, Black
Part No. RW3U600BK



Ideal for hallways, stairways, bathrooms, living and dining rooms and other areas with multiple entrances, this occupancy/vacancy sensor allows true multi-way operation with automatic ON/OFF control.

Features & Benefits

- Occupancy-based control plus multi-way operation.
 - Two or more RW3U600 sensors connected together will allow enhanced coverage of the controlled space.
 - Works with most common types of residential lighting.
 - Adjustable time delay of 15 seconds to 30 minutes.
 - Light-level sensing prevents automatic ON of lights when adequate daylight exists.
 - Replaces 3-way or 4-way switches when used with other RW3U600 sensors.
 - Lighted switch for visibility in darkened rooms.
 - Manual- or automatic-ON operation.
 - Adjustable light level setting of 10 to 150 fc (100 to 1500 lux). Coverage: 180 degrees, max. 600 ft.2 (56m2).
 - Load: Incandescent, Fluorescent, Compact Fluorescent (CFL), Magnetic Low-Voltage (MLV) and Electronic Low-Voltage (ELV) 1/6 hp.
- For covering patents, see www.legrand.us/patents.

Specifications

General Info

Product Line	Pass & Seymour	Replaced by Part Number	RW3U600BKCC4
Country Of Origin	China		

Technical Information

Sensor Type	Occupancy, Vacancy	Wattage	600 W
Voltage	120.0 V		