



Wattstopper
Vacancy Sensor, 3-wire w/Nightlight, White
Part No. RS-150BA-N-W



The RS-150BA-N Passive Infrared (PIR) Vacancy Sensor provides automatic shutoff for single-pole lighting control applications. It is engineered to comply with specific provisions of California's Title 24-2013 energy code.

Features & Benefits

| | |
|---|--|
| Complies with 2011 NEC requirements | Integral LED nightlight |
| Relay-based switching | Replaces single-pole switches |
| Fixed 30-minute time delay; no adjustment necessary | Amber LED nightlight illuminates whenever connected load is off |
| Low-profile styling | Choice of five decorator colors; lens is color-matched to device |
| Manual-on/automatic-off control | Ideal for bathrooms |
| Integral LED nightlight | Fixed 30-minute time delay |

Specifications

General Info

| | | | |
|--------------------|--|-------------------|---------------|
| Product Line | Wattstopper | Color | White |
| UPC Number | 754182917280 | Country Of Origin | China |
| Features | IR (Infrared), Motion Sensor, Nightlight | Switch Type | Motion Sensor |
| Application Sector | Commercial | Warranty Type | 5-Year |

Dimensions

| | | | |
|-------------------|------------|-------------------|--------|
| Product Width US | 4.0 in | Product Weight US | 0.3 lb |
| Product Volume US | 63.0 cu in | Product Depth US | 5.0 in |
| Product Height US | 3.15 in | | |

Additional Information

| | | | |
|-----------------|-----|--|-----|
| RoHS Conformant | Yes | DesignLights Consortium Qualified System | Yes |
|-----------------|-----|--|-----|

| | |
|----------|-----|
| Security | Yes |
|----------|-----|

Technical Information

| | | | |
|--------------------|-------|-------------|---------|
| Response Frequency | 60 Hz | Sensor Type | Vacancy |
|--------------------|-------|-------------|---------|

| | | | |
|-------------------|---|----------|-----|
| Number of Buttons | 1 | Amperage | 5 A |
|-------------------|---|----------|-----|

| | | | |
|-----------|-----------|---------|-------|
| Indicator | LED Light | Wattage | 600 W |
|-----------|-----------|---------|-------|

| | | | |
|---------------|------------------------|---------|---------|
| Sensing Range | 600 sq ft, 180 degrees | Voltage | 120.0 V |
|---------------|------------------------|---------|---------|

| | |
|-----------------|-------|
| Connection Type | Wired |
|-----------------|-------|
