

Wattstopper Time Switch, 7-Button Countdown, Lt. Almond Part No. RT-50-LA

The RT-50 Preset Countdown Time Switch automatically turns lighting or other loads off when the selected on-time expires. It replaces standard single-pole wall switches for energy savings throughout a range of applications.

Features & Benefits

Seven-button preset time switch	Easy operation and precise time countdown
Replaces single-pole switch	Selectable on-time: 1, 5, 10, 20, 30, 60 minutes
Lighted switch for visibility in darkened rooms	Zero crossing reduces stress on the relay and increases product longevity
No current leakage to load in off mode for safety	Relay-based switching
Pushbutton switch for automatic-off control	Ideal for closets, laundry rooms, pantries and storage areas
Easy operation and precise time countdown	Choice of six preset on-times from 1 minute to 60 minutes

Specifications

General Info

Wattstopper Light Almond China	Replaced by Part Number UPC Number Features	RT-20-LA 754182918263 Locator
		Locator
China	Features	
		Light, Timer
Push	Application Sector	Commercial
5-Year		
2.0 in	Product Weight US	0.3 lb
	5-Year	5-Year

Liming Range						
Additional Information RoHS Conformant Yes Security Yes Technical Information Number of Buttons 7	27.84 cu in	Product Depth US	4.5 in			
RoHS Conformant Yes Security Yes Technical Information Number of Buttons 7 Timing Range	2.25 in					
Security Yes Technical Information Number of Buttons 7 Timing Range	Additional Information					
Technical Information Number of Buttons 7 Timing Range	/es	DesignLights Consortium Qualified System	Yes			
Number of Buttons 7	′es					
Timing Range	Technical Information					
liming Kange	7	Amperage	5 A			
	10 minutes, 5 minutes, 30 minutes, 20 minutes, 1 minute, 60 minutes	Wattage	600 W			
Voltage 120.	20.0 V	Connection Type	Wired			